

XFD680 Anti-mouse CD26 Antibody *H194-112, XFD680 Same Structure to Alexa Fluor™ 680*

Catalog number: 10260190, 10260191

Unit size: 100 tests, 500 tests

Product Details

Storage Conditions 2-8°C with minimized light exposure. Do not freeze.

Expiration Date 12 months upon receiving

Concentration 0.1 mg/mL

Formulation Phosphate-buffered saline (PBS, pH 7.2), 0.09% sodium azide, 0.2% (w/v) BSA

Antibody Properties

Species Reactivity Mouse

Class Primary

Clonality Monoclonal

Host Rat

Isotype Rat IgG2a kappa

Immunogen CD26 (DPP IV ectoenzyme, ADA-binding protein, ADCP2)

Clone H194-112

Conjugate AF680

Biological Properties

Appearance liquid

Preparation Antibody purified by affinity chromatography and then conjugated with AF680 under optimal

conditions

Application Flow Cytometry (FACS), Fluorescence Imaging

Spectral Properties

Conjugate AF680

Excitation Wavelength 681 nm

Emission Wavelength 704 nm

Applications

H194-112 is an anti-mouse monoclonal antibody that recognizes the CD26 antigen. CD26 (also known as DPP IV ectoenzyme, ADA-binding protein or ADCP2) is a 110 kD glycoprotein that is located on the surface of cells such as macrophages and NK cells. In some organisms, CD26 is an enhancer of cell population proliferation and plays a role in the downregulation of extracellular matrix disassembly, and is associated with a variety of biologically interesting macromolecules/ligands, namely, CD45, collagen and adenosine deaminase. CD26 is a fairly uncommon antibody target, with a little more than 3500 publications in the last decade. Even still, CD26 is frequently used in flow cytometry applications as a phenotypic marker for differentiation of cell types, particularly in the study of immunology. This antibody was purified through affinity chromatography and conjugated to XFD680 (ex/em = 681/704 nm). XFD680 is manufactured by AAT Bioquest, and it has the same chemical structure of Alexa Fluor® 680 (Alexa Fluor® is the trademark of ThermoFisher). It is compatible with the 642 nm laser and 702/85 nm bandpass filter (for example, as in the Luminex Amnis ImageStream).